

1. Im Webbrowser (Internet Explorer, Safari, Firefox, Chrome, etc.) die Adresse: **http://192.168.0.1** eingeben.
2. Die Felder **User Name** und **Password** leer lassen und auf **Log In** klicken.

The screenshot shows the Cisco EPC3925 web interface. At the top, it says "Cisco EPC3925 EuroDocsis 3.0 2-PORT Voice Gateway" and "EPC3925". Below the header, there is a "Status" tab. A navigation bar contains "Gateway", "Local Network", "Wireless", "DOCSIS WAN", and "Channels Selection". The "Log In" page is displayed, featuring a "Log In" sidebar on the left. The main content area has three input fields: "User Name:", "Password:", and "Language Selection" (set to "English"). A "Log In" button is highlighted with a red box.

3. Unter **Setup – Quick Setup** kann der **Wireless Network Name (SSID)** sowie der **Pre-Shared Key** geändert werden. Mit einem Klick auf **Save Settings** werden die Änderungen gespeichert.

The screenshot shows the Cisco EPC3925 web interface. At the top, it says "Cisco EPC3925 EuroDocsis 3.0 2-PORT Voice Gateway" and "EPC3925". Below the header, there is a "Setup" tab. A navigation bar contains "Wireless", "Security", "Access Restrictions", "Applications & Gaming", "Administration", "Status", "Voice", and "Log OFF". The "Quick Setup" page is displayed, featuring a "Change Password" sidebar on the left. The main content area has three input fields: "User Name:", "Change Password to:", and "Re-Enter New Password:". Below these, there is a "Wireless Network" section with "Wireless Network Name (SSID)" set to "8a08aa" and "Wireless Security Mode" set to "WPA or WPA2-Personal". The "Encryption" is set to "TKIP + AES". A "Pre-Shared Key" field is highlighted with a red box. At the bottom, there are "Save Settings" and "Cancel Changes" buttons, with "Save Settings" highlighted by a red box.